

from high-performance steel, bearings have a limited service life. Indeed, the loads applied to bearings will eventually result in fatigue failure of the material which limits the service life. However, on top of the fatigue failures, many other external factors to the bearings influence the life and can lead to

premature failure.

Bearings are a wearing part and will fail eventually. Despite being machined to very close tolerances

With extensive experience in fault diagnosis and prevention in relation to bearings, NTN-SNR wishes to share its expertise with you. Being able to distinguish between natural fatigue and abnormal failure, you will then be able to make the most of our products and thus boost performance.

PRINCIPALES CAUSES D'AVARIES

- 1 Corrosion by oxidation
- 2 Fretting corrosion
- 5 False brinelling
- 4 Surface spalling initiated at the surface (ÉSIS)
- 5 Deep spalling initiated at the surface (ÉPIS)
- Deep spalling initiated at a depth (ÉPIP)
- 7 Electro-erosion

- 8 Plastic deformation
- 9 Rupture
- 10 Wear under the action of particles
- 11 Wear by friction
- 12 Spalling by axial overload
- 13 Indentations

GENERAL RECOMMENDATIONS

- Store the bearings flat in an air-conditioned room
- Avoid stacking cardboard boxes with heavy bearings
- Use NTN-SNR range methods and tools
- Check and respect the mounting adjustments
- Refer to the plans and assembly drawings

- Work in clean conditions
- Lubricate the bearings with the correct amount of grease before commissioning
- Ensure the effectiveness of the sealing devices



CORROSION BY OXIDATION

OBSERVATION

Marks or pits

CAUSE

 Pollution by water, old oil, hydraulic fluid or aggressive additives

- Purge the bearings and remove the old lubricants
- Avoid water contacting the bearings



FRETTING CORROSION

OBSERVATION

• Oxide layer on the outer surfaces of the bearing

CAUSE

• Microscopic displacement between ring and suppor

- Check the precision and seat adjustments
- Use NTN-SNR anti-fretting paste and an induction heater to install the bearing on the shaft



3 FALSE BRINELLING

OBSERVATION

 Corrosion due to friction between rolling elements and raceways

CAUSE

• In the static state, vibrations or oscillations shear the oil film

- Avoid storing stationary rotating machines near sources of vibration such as a compressor or vibrating unit.
- The bearings must be stored flat



SURFACE SPALLING INITIATED AT THE SURFACE (ÉSIS)

OBSERVATION

• Surface spalling initiated at the surface

CAUSES

- Inadequate lubrication (quantity/quality)
- Rupture of the oil film
- Presence of small, very fine and hard particles

- Check the temperature level
- Choose a suitable lubricant (quantity and viscosity) as well as an automatic lubrication system
- Avoid the intrusion of solid particles and liquids during and after mounting



DEEP SPALLING INITIATED AT A DEPTH (ÉPIP)

OBSERVATION

 Spalling initiated on a surface defect (indentation, impact, corrosion, excess stress, etc.)

CAUSES

- Solid contamination
- Impact
- · Entry of corrosive liquid
- Misalignment or deformation of the housing or the shaft

- Avoid introducing contaminants when mounting
- Control the geometry and quality of seats to avoid stresses due to misalignment in the bearings



DEEP SPALLING INITIATED AT A DEPTH (ÉPIP)

OBSERVATION

• Spalling that is generally elliptical

CAUSE

• Cyclic stresses (causing the natural death of the bearing due to fatigue)

- Use a monitoring system on equipment to detect vibrations and noises associated with the start of spalling due to fatique
- Follow a predictive maintenance schedule for bearing replacement
- Make sure the bearing is compatible



TELECTRO-EROSION

OBSERVATION

• Pits or grooves

CAUSES

• An electric current passing through a bearing

NTN-SNR RECOMMENDATION

 Make sure electric currents do not pass through the bearing.
 For generator and electric motor applications, choose NTN-SNR MEGAOHM insulated bearings



PLASTIC DEFORMATION


OBSERVATION

• Marks from rolling housings on raceways

CAUSE

• Incorrect mounting or significant and short overload

- Use the correct mounting method and NTN-SNR tools
- Ensure rolling elements do not transmit a static overload



OBSERVATION

• Ring rupture

CAUSES

• Shocks, overload, bending force, fatigue or thermal overstresses

- Never strike a bearing directly with a hammer
- Check the conditon of the seats before mounting
- Use the correct mounting method and suitable NTN-SNR tools
- Quickly replace a noisy bearing



WEAR UNDER THE ACTION OF PARTICLES

OBSERVATION

 Matt surface, streaks or pits on rolling housings and raceways

CAUSES

• Solid particle abrasion in boundary lubrication

- Choose an NTN-SNR sealing device that is effective against the penetration of solid particles (seals, shields)
- Make sure to use a clean lubricant for maintenance
- Use a lubricant



WEAR BY FRICTION

OBSERVATION

Metal elements welded to one another

Cause

• Significant sliding due to temperature rise

NTN-SNR RECOMMENDATION

 UUse a suitable lubricant in terms of quantity and quality and a suitable bearing in terms of load and speed



SPALLING BY AXIAL OVERLOAD

OBSERVATION

 Presence of spalling on one side of the bearing raceways

CAUSE

Excessive axial load

NTN-SNR RECOMMENDATION

• Check the floating bearing is free to move



13 INDENTATIONS

OBSERVATION

 Holes on the surface of the raceway by rolling hard particles between rolling elements and raceways under load

CAUSE

• Pollution of the lubricant with hard particle

NTN-SNR RECOMMENDATION

• Identify the origin of the pollution: metal chips in the lubricant, spalled bearing, etc.









This document is the exclusive property of NTN-SNR ROULEMENTS. Any total or partial reproduction hereof without the prior consent of NTN-SNR ROULEMENTS is strictly prohibited. Legal action may be brought against anyone breaching the terms of this paragraph.

of this paragraph.

NTH-SNR ROULEMENTS shall not be held liable for any errors or omissions that may have crept into this document despite the care taken in drafting it. Due to our policy of continuous research and development, we reserve the right to make changes without notice to all or part of the products and specifications mentioned in this document.

NTN-SNR ROULEMENTS, international copyright 2019.









